Distributed by:

JAMECO® ELECTRONICS

www.Jameco.com ✦ 1-800-831-4242

The content and copyrights of the attached material are the property of its owner.

FAIRCHILD SEMICONDUCTOR™

Jameco Part Number 25831

MJE2955T

General Purpose and Switching Applications

- DC Current Gain Specified to I_C = 10 A
- High Current Gain Bandwidth Product : f_T = 2MHz (Min.)



TO-220

1.Base 2.Collector 3.Emitter

PNP Silicon Transistor

Absolute Maximum Ratings T_C=25°C unless otherwise noted

Symbol	Parameter	Value	Units
V_{CBO}	Collector-Base Voltage	- 70	V
V_{CEO}	Collector-Emitter Voltage	- 60	V
V_{EBO}	Emitter-Base Voltage	- 5	V
I_C	Collector Current	- 10	A
I_B	Base Current	- 6	A
P_C	Collector Dissipation (T_C=25°C)	75	W
P_C	Collector Dissipation (T_a=25°C)	0.6	W
T_J	Junction Temperature	150	°C
T_{STG}	Storage Temperature	- 55 ~ 150	°C

Electrical Characteristics T_C=25°C unless otherwise noted

Symbol	Parameter	Test Condition	Min.	Max.	Units
BV_{CEO}	Collector- Emitter Breakdown Voltage	I_C= - 200mA, I_B = 0	-60		V
I_{CEO}	Collector Cut-off Current	V_{CE} = - 30V, I_B = 0		-700	μA
I_{CEX1}	Collector Cut-off Current	V_{CE} = - 70V, V_{BE}(off) = 1.5V		-1	mA
I_{CEX2}	Collector Cut-off Current	V_{CE} = - 70V, V_{BE}(off) = 1.5V @ T_C = 150°C		-5	mA
I_{EBO}	Emitter Cut-off Current	V_{EB} = - 5V, I_C = 0		-5	mA
h_{FE}	* DC Current Gain	V_{CE} = - 4V, I_C = - 4A V_{CE} = - 4V, I_C = - 10A	20 5	100	
V_{CE}(sat)	* Collector-Emitter Saturation Voltage	I_C = - 4A, I_B = - 0.4A I_C = - 10A, I_B = - 3.3A		-1.1 -8	V V
V_{BE} (on)	* Base-Emitter ON Voltage	V_{CE} = - 4V, I_C = - 4A		-1.8	V
f_T	Current Gain Bandwidth Product	V_{CE} = - 10V, I_C = - 500mA	2		MHz

* Pulse test: PW≤300μs, duty cycle≤2% Pulse

©2001 Fairchild Semiconductor Corporation

Typical Characteristic



Figure 1. DC current Gain



Figure 2. Base-Emitter Saturation Voltage Collector-Emitter Saturation Voltage



Figure 3. Safe Operating Area



Figure 4. Power Derating

©2001 Fairchild Semiconductor Corporation

Package Demensions

TO-220



Dimensions in Millimeters

©2001 Fairchild Semiconductor Corporation

TRADEMARKS

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx™
Bottomless™
CoolFET™
CROSSVOLT™
DOME™
E^2CMOS™
EnSigna™
FACT™
FACT Quiet Series™
FAST®
FASTr™
GlobalOptoisolator™
GTO™
HiSeC™
ISOPLANAR™
MICROWIRE™
OPTOLOGIC™
OPTOPLANAR™
PACMAN™
POP™
PowerTrench®
QFET™
QS™
QT Optoelectronics™
Quiet Series™
LILENT SWITCHER®
SMART START™
SuperSOT™-3
SuperSOT™-6
SuperSOT™-8
SyncFET™
TinyLogic™
VCX™
UHC™

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR INTERNATIONAL.

As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.

2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

PRODUCT STATUS DEFINITIONS

Definition of Terms

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

©2001 Fairchild Semiconductor Corporation